

## I<sup>2</sup>S Output MEMS Microphone Flex Evaluation Board

### GENERAL DESCRIPTION

This user guide applies to the following MEMS microphone evaluation boards:

- EV\_ICS-43434-FX

This is a simple board that allows quick evaluation of the performance of the ICS-43434 MEMS microphone. The small size and low profile of the flexible PCB enables direct placement of the microphone into a prototype or an existing design for an in situ evaluation. The board consists of an I<sup>2</sup>S-output microphone soldered to a flexible PCB. The only other component on the board is a 0.1 μF supply bypass capacitor.

The flex PCB design mates to a 6-position ZIF connector with 0.5 mm pin spacing, such as the Molex 0527450697 connector. The flex PCB mates to the connector by first pulling out the connector’s clamp, inserting the flex PCB, and then pushing the clamp closed. Wires can be soldered directly to this connector’s pins or it can be mounted directly on a rigid PCB for evaluation. We recommend to use 28 AWG or smaller wire for soldering to this connector’s pins. The PCB thickness at the pin edge is 0.3 mm.

### TABLE 1. PIN FUNCTION DESCRIPTIONS

Flex PCB pad (Top to Bottom, see Figure 2)	Mic Pin	Description
1	LR	Left/right channel select
2	WS	Word select for I <sup>2</sup> S interface
3	SD	Serial digital output signal for I <sup>2</sup> S interface
4	SCK	Serial clock for I <sup>2</sup> S interface
5	VDD	Power, 1.62 to 3.63 V
6	GND	Ground

### EVALUATION BOARD CIRCUIT

Figure 1 show the schematics of the evaluation board, and Figure 2 shows the board layout. See the microphone data sheets for complete descriptions and specifications.




Figure 1. EV\_ICS-43434-FX Evaluation Board Schematic



Figure 2. EV\_ICS-43434-FX Evaluation Board Layout (Top View)




Figure 3. Evaluation Board Dimensions in Millimeters

**EVALUATION BOARD PHOTOGRAPHS**




Figure 4. EV\_ICS-43434-FX Top View



Figure 5. EV\_ICS-43434-FX Bottom View

**REVISION HISTORY**

Revision Date	Revision	Description
4/26/2016	1.0	Initial Release

---

**COMPLIANCE DECLARATION DISCLAIMER**

InvenSense believes the environmental and other compliance information given in this document to be correct but cannot guarantee accuracy or completeness. Conformity documents substantiating the specifications and component characteristics are on file. InvenSense subcontracts manufacturing, and the information contained herein is based on data received from vendors and suppliers, which has not been validated by InvenSense.

This information furnished by InvenSense is believed to be accurate and reliable. However, no responsibility is assumed by InvenSense for its use, or for any infringements of patents or other rights of third parties that may result from its use. Specifications are subject to change without notice. InvenSense reserves the right to make changes to this product, including its circuits and software, in order to improve its design and/or performance, without prior notice. InvenSense makes no warranties, neither expressed nor implied, regarding the information and specifications contained in this document. InvenSense assumes no responsibility for any claims or damages arising from information contained in this document, or from the use of products and services detailed therein. This includes, but is not limited to, claims or damages based on the infringement of patents, copyrights, mask work and/or other intellectual property rights.

Certain intellectual property owned by InvenSense and described in this document is patent protected. No license is granted by implication or otherwise under any patent or patent rights of InvenSense. This publication supersedes and replaces all information previously supplied. Trademarks that are registered trademarks are the property of their respective companies. InvenSense sensors should not be used or sold in the development, storage, production or utilization of any conventional or mass-destructive weapons or for any other weapons or life threatening applications, as well as in any other life critical applications such as medical equipment, transportation, aerospace and nuclear instruments, undersea equipment, power plant equipment, disaster prevention and crime prevention equipment.

©2016 InvenSense, Inc. All rights reserved. InvenSense, MotionTracking, MotionProcessing, MotionProcessor, MotionFusion, MotionApps, Digital Motion Processor, AAR and the InvenSense logo are trademarks of InvenSense, Inc. Other company and product names may be trademarks of the respective companies with which they are associated.



©2016 InvenSense, Inc. All rights reserved.